# Product Specifications PROVEN DATA LOGGING SOLUTIONS



# **SmartReader Plus 7**

## Eight-Channel Process Signal Data Logger

The SmartReader Plus 7 data logger is a versatile data logger for easy recording of common process signal variables. With seven input channels, the logger is ideal for monitoring (through commercially available transducers) a wide variety of measurement parameters.)

#### **APPLICATIONS**

Monitoring wind speed, flow, tank level, pressure, current, voltage, power, SCADA troubleshooting, etc.

#### **GENERAL SPECIFICATIONS**

 $\begin{array}{lll} \text{Size:} & 107\text{mm} \times 74\text{mm} \times 22\text{mm} \ (4.2'' \times 2.9'' \times 0.9'') \\ \text{Weight:} & 110 \ \text{g} \ (3.75 \ \text{oz}) \\ \text{Case Material:} & \text{Noryl}^{\circledR} \ \text{Plastic} \\ \text{Battery:} & 3.6 \ \text{volt Lithium} \\ \text{Resolution:} & 12\text{-bit} \ (1 \ \text{part in } 4096) \\ \text{Mounting:} & \text{Magnetic backing or locking eyelet} \\ \end{array}$ 

Clock Accuracy: ± 2 seconds per day

Sampling Methods: Continuous (First-in First-out)\*, Stop When Full (Fill-then-stop)

\*Not available with sample rates faster than eight seconds

Operating Limits: -40°C to 70°C (-40°F to 158°F) and 0 to 95% RH (non-condensing)

PC Requirements: Windows PC with at least one free USB or serial port (depending on interface)
Software Requirements: TrendReader® 2 (Compatible with Windows 2000 SP4, XP SP1 and Vista 32 bit)

Software Requirements: TrendReader® 2 (Compatible with Windows 2000 SP4, XP SP1 and Vista Memory Size: 32 KB (capable of storing up to 21,500 readings)

(3 memory sizes available)

128 KB (capable of storing up to 87,000 readings)

1.5 MB (capable of storing up to 1,048,000 readings)

Sampling Rates: User selectable rates from 25 per second to once every eight hours (BP-101

battery pack or PS-201 power supply required for sampling rates faster than

eight seconds)

Number of Channels: Eight (One for the internal temperature sensor and seven external channels for analog voltage and current loop signals.)

#### SENSOR SPECIFICATIONS

#### **Internal Temperature Sensor**

Type: NTC Thermistor - 10,000 Ohm @  $25^{\circ}$ C ( $77^{\circ}$ F)

Range:  $-40^{\circ}$ C to  $70^{\circ}$ C ( $-40^{\circ}$ F to  $158^{\circ}$ F)

Accuracy:  $\pm 0.2^{\circ}$ C over the range of  $0^{\circ}$ C to  $70^{\circ}$ C ( $\pm 0.3^{\circ}$ F over the range of  $32^{\circ}$ F to  $158^{\circ}$ F)

Recolution:  $0.23^{\circ}$ C ( $0.05^{\circ}$ F) @  $35^{\circ}$ C; bottor than  $0.07^{\circ}$ C ( $0.13^{\circ}$ F) between  $-35^{\circ}$ C and  $70^{\circ}$ C

Resolution:  $\pm 0.2^{\circ}\text{C}$  over the range of  $0^{\circ}\text{C}$  to  $70^{\circ}\text{C}$  ( $\pm 0.3^{\circ}\text{F}$  over the range of  $32^{\circ}\text{F}$  to  $158^{\circ}\text{F}$ );  $0.03^{\circ}\text{C}$  ( $0.05^{\circ}\text{F}$ ) @  $25^{\circ}\text{C}$ ; better than  $0.07^{\circ}\text{C}$  ( $0.12^{\circ}\text{F}$ ) between  $-25^{\circ}\text{C}$  and  $70^{\circ}\text{C}$  ( $-13^{\circ}\text{F}$  and  $158^{\circ}\text{F}$ ); better than  $0.13^{\circ}\text{C}$  ( $0.23^{\circ}\text{F}$ ) between  $-40^{\circ}\text{C}$  and  $-25^{\circ}\text{C}$ 

(-40°F and -13°F)

#### Standard Model (SRP-007)

### Input Range\*

0 to 2.5V DC (1 channel) 0 to 5V DC (2 channels) 0 to 10V DC (1 channel) 0 to 200mV DC (1 channel) 0 to 25mA DC (2 channels)

## Other Models

#### Input Range\*

All external channels: 0 to 2.5V DC (SRP-007-0-2.5V)
All external channels: 0 to 5V DC (SRP-007-0-5V)
All external channels: 0 to 10V DC (SRP-007-0-10V)
All external channels: 0 to 25mA (SRP-007-25mA)

#### **Maximum Protection**

Voltage channels: ± 40V (reverse-polarity protected)
Current channels: ± 70mA (reverse-polarity protected)

Accuracy: ±0.5% of full scale

#### Input Impedance

>1M Ohm (200mV channel) >1M Ohm (0 to 2.5V channel) >1M Ohm (0 to 5V channel) >1M Ohm (0 to 10V channel) 20 Ohm (0 to 25mA channel)

<sup>\*</sup>Transducer restrictions: The use of a single power supply is recommended to avoid ground loops or use loop isolators.